

How to Use aIOS WGB with EAP-TLS Authentication in a Cisco Unified Wireless Network

Contents

[Introduction](#)

[Prerequisites](#)

[Requirements](#)

[Components Used](#)

[Conventions](#)

[Configuration Overview](#)

[Configure](#)

[Bring up the Microsoft CA \(If Necessary\)](#)

[Install the Server Certificate in the ACS](#)

[Install the CA Certificate on the ACS](#)

[Setup the ACS to Use the Server Certificate](#)

[Configure ACS to Let the WGB authenticate in EAP-TLS](#)

[Configure the WLAN of the WLC to Authenticate to ACS](#)

[Configure the Certificates of the WGB](#)

[Configure the WGB SSID, Supplicant and Radio as Needed](#)

[Configure Entries for a Passive Client \(If Necessary\)](#)

[Special Notes if 802.11a \(5 GHz\) is Used](#)

[Configurations](#)

[Synchronize the Cisco IOS supplicant's clock and save its time to NVRAM \(for systems with Cisco IOS Software Release 12.4\(21a\)JY\)](#)

[Verify](#)

[Troubleshoot](#)

[Troubleshooting Commands](#)

[Related Information](#)

[Introduction](#)

This example shows how to configure and use an autonomous IOS (aIOS) AP, running in Workgroup Bridge (WGB) mode, with EAP-TLS authentication, in a Cisco Unified Wireless Network (CUWN). In this example, a Microsoft Certification Authority (Windows 2003) issued the certificates of the WGB and through the copy-and-paste method, these certificates are manually entered on the WGB. ACS acts as the RADIUS server. WPA1/TKIP encryption with 802.1X key management is used.

Prerequisites

Requirements

Ensure that you meet these requirements before you attempt this configuration:

- Knowledge of Cisco Autonomous solution and Cisco IOS-based Access Points.
- Knowledge of Light Weight Access Point Protocol (LWAPP)

Components Used

The information in this document is based on these software and hardware versions:

- WGB that runs Cisco IOS® Software Release 12.4(10b)JA2It is important to use Cisco IOS Software Release 12.4(10b)JA2 or later for these reasons: Cisco bug ID [CSCsl85710](#) ([registered](#) customers only) —802.11a WGB cannot disable DFS channels or enable 'mobile station' Cisco bug ID [CSCsl85798](#) ([registered](#) customers only) —After DFS event, WGB does not rescan Cisco bug ID [CSCsm37686](#) ([registered](#) customers only) —WGB configured for TKIP-only cannot assoc to (WPA+TKIP)+(WPA2+AES) Cisco bug ID [CSCsk85945](#) ([registered](#) customers only) —WPA1 WGB can't associate to a WPA1+WPA2 WLAN Cisco bug ID [CSCsk52437](#) ([registered](#) customers only) —WGB retransmit fails when AP goes offchannel Cisco bug ID [CSCsb85791](#) ([registered](#) customers only) —1130 crashes just after installation of the new image Cisco bug ID [CSCsk63882](#) ([registered](#) customers only) —Bad Id error with traceback seen when 12.4-Based 802.11 AP comes up Cisco bug ID [CSCsl36227](#) ([registered](#) customers only) —Tracebacks on WGB: %SM-4-BADEVENT: Event 'eapResp' is invalid Cisco bug ID [CSCsl46209](#) ([registered](#) customers only) —WGB 1242 11g radio stuck in reset, stops transmitting Cisco bug ID [CSCsl58071](#) ([registered](#) customers only) —WGB intermittently takes a long time to reauthenticate in EAP-TLS
- WLC that runs version 4.2.99.0It is important to use 4.1.185.0 or later for this reason: Cisco bug ID [CSCsk41360](#) ([registered](#) customers only) —Controller continues processing EAPOL LOGOFF after receiving EAPOL

Note: You need to be a [registered](#) customer in order to view the details of the bug.

The ACS was running 4.1; the CA was running Microsoft Windows 2003 Advanced Server SP1. In all cases, when you browsed to the CA, the client browser was Internet Explorer with Active X enabled.

The information in this document was created from the devices in a specific lab environment. All of the devices used in this document started with a cleared (default) configuration. If your network is live, make sure that you understand the potential impact of any command.

Conventions

Refer to the [Cisco Technical Tips Conventions](#) for more information on document conventions.

Configuration Overview

1. [Bring up the Microsoft CA \(If Necessary\)](#)
2. [Install the Server Certificate in the ACS](#)
3. [Install the CA Certificate on the ACS](#)
4. [Setup the ACS to Use the Server Certificate](#)
5. [Configure ACS to let the WGB authenticate in EAP-TLS](#)
6. [Configure the WLAN of the WLC to Authenticate to ACS](#)
7. [Configure the Certificates of the WGB](#) Set the hostname, domain name and time as needed. Configure the trustpoint. Install the CA certificate. Generate the AP certificate request. Send the AP certificate request to the CA. Issue the certificate. Install the AP certificate.
8. [Configure the WGB SSID, Supplicant and Radio as Needed](#)
9. [Configure Entries for a Passive Client \(If Necessary\)](#)
10. [Special Notes if 802.11a \(5 GHz\) is Used](#)
11. [Synchronize the Cisco IOS supplicant's clock and save its time to NVRAM \(for systems with Cisco IOS Software Release 12.4\(21a\)JY\)](#)

[Configure](#)

In this section, you are presented with the information to configure the features described in this document.

Note: Use the [Command Lookup Tool](#) ([registered](#) customers only) in order to obtain more information on the commands used in this section.

[Bring up the Microsoft CA \(If Necessary\)](#)

Complete these steps in order to open the Microsoft CA with the use of Windows 2003 Advanced Server:

1. First, have IIS installed. Choose **Control Panel > Add/Remove Programs > Windows Components > Application Server**.
2. Then, install the CA. Choose **Control Panel > Add Remove Programs > Windows Components > Certificate Services**. Choose an **Enterprise Root CA**. Give the CA a name, and make a note of it.

[Install the Server Certificate in the ACS](#)

Complete these steps in order to install the server certificate in the ACS.

1. From a browser that runs on the ACS server, browse to the CA:
http://ip.of.CA.server/certsrv Request a **Certificate > Advanced Request > Create and Submit a request to this CA**. In the Name (CN) field, enter something. Make a note of it. In the Type of Certificate Needed drop-down menu, choose **Server Authentication Certificate**. Under key options, choose: **CSP — Microsoft Base Cryptographic Provider v1.0** Key size — **1024** Check **Mark keys as exportable**. Check **Store cert in the local computer cert store**. Leave everything else as default, and click **Submit**. You should see a `Certificate Pending` status report that says `Your certificate request has been received`. If you have a problem, see MS KB 323172, or other things that can get in the way of Active X.

2. Now, on the CA, go into the CA admin utility and choose **Start > Administrative Tools > Certification Authority**. On the left, expand the CA icon, and look under Pending Requests. On the right, right-click the request from the ACS and choose **All Tasks > Issue**. The request should now appear under Issued Certificates.
3. Back on the ACS server, browse again to **http://ip.of.CA.server/certsrv**. Click **View the status of a pending certificate request**. Click **Server Authentication Certificate**. Click **Install this certificate**.

[Install the CA Certificate on the ACS](#)

Complete these steps:

From a browser that runs on the ACS server, browse to the CA: **http://ip.of.CA.server/certsrv**

1. Click **Download a CA certificate, certificate chain, or CRL**.
2. Choose **Encoding method: Base 64**.
3. Choose **Download CA certificate**.
4. Open the .cer file, then click **Install Certificate**.
5. In the Certificate Import Wizard, click **Next**, then **Place all certificates in the following store**, then **Browse**.
6. Check the **Show physical stores** box.
7. Expand **Trusted root certification authorities**, choose **Local Computer**, and click **Ok**.
8. Click **Next, FINISH**, and **OK** for `The import was successful` box.

[Setup the ACS to Use the Server Certificate](#)

Complete these steps:

1. On the ACS server, choose **System Configuration**.
2. Choose **ACS Certificate Setup**.
3. Choose **Install ACS certificate**.
4. Choose **Use certificate from storage**.
5. Type in the CN name, the same name that was used in a previous step.
6. Click **Submit**.
7. In the ACS server, click **System configuration**.
8. Choose **ACS Certificate Setup**.
9. Choose **Edit Certificate Trust List**.
10. Check the box for the CA.
11. Click **Submit**.

[Configure ACS to Let the WGB authenticate in EAP-TLS](#)

Complete these steps in order to configure the ACS to let the WGB authenticate in ACS:

1. Add the WLC as a NAS (AAA client). In the ACS GUI, click **Network Configuration** on the left. Under AAA Clients, click **Add Entry**. Enter a name under AAA Client Hostname. Enter the management interface IP address of the WLC under AAA Client IP Address. Enter the RADIUS key under Shared Secret and make a note of it. In the Authenticate Using drop-down

- menu, choose **RADIUS (Cisco Airespace)**. Click **Submit+Apply**.
2. Enable EAP-TLS in ACS. Choose **System Configuration > Global Authentication Setup**. Under EAP-TLS, for example, the top-level EAP-TLS, after EAP-FAST, not the EAP-TLS under PEAP, check **Allow EAP-TLS**. Check all three of the certificate verification options. Choose **Submit + Restart**.
 3. Add the WGB as an ACS. In User Setup, enter the name of the WGB in the User panel, and click **Add/Edit**. This example uses "WGB". Enter a hard-to-guess password. This is required, although not used in EAP-TLS. Click **Submit**.

[Configure the WLAN of the WLC to Authenticate to ACS](#)

Complete these steps:

1. Browse to the GUI of the WLC.
2. Add the ACS to the RADIUS server list: Choose **Security > AAA > RADIUS > Authentication** and click **New**. Enter the ACS IP address in the Server IP Address panel. Enter the RADIUS shared secret from the previous step. Click **Apply**.
3. Add a WLAN for the EAP-TLS clients: Under WLANs, click **New**. Enter the SSID as the Profile Name and the WLAN SSID. In the General tab, check the **Enabled** checkbox, and Broadcast SSID (as desired). Under the Security tab: Under the Layer 2 tab, choose **WPA+WPA2** in the Layer 2 Security drop-down menu, check **WPA Policy with TKIP encryption**, uncheck **WPA2 policy with AES encryption**, and choose **802.1X for Auth Key Mgmt**. Under the AAA Servers, add the ACS, unless the ACS is the global default RADIUS server. Click **Apply**.

[Configure the Certificates of the WGB](#)

Complete these steps:

Note: This method uses the copy-and-paste method. Refer to [Configuring Certificates Using the crypto pki CLI](#) in the *Cisco 3200 Series Wireless MIC Software Configuration Guide* for more information on how to use the TFTP and SCEP methods.

1. Set the hostname, domain name and time of the WGB as needed. The hostname must match the username entered for it in ACS as in the previous [step](#):

```
ap#configure terminal
ap(config)#hostname WGB
WGB(config)#
```

The time must be correct, for the certifications to work (clock set exec CLI, or configure an sntp server).

2. Configure the trustpoint for the CA:

```
WGB#config term
WGB(config)#crypto pki trustpoint CUT-PASTE
WGB(config)#enrollment terminal
WGB(config)#subject-name CN=WGB
```

Note: `subject-name CN=<ClientName>` is required. Without it, the Microsoft CA fails to issue the cert, with the `The request subject name is invalid or too long. 0x80094001` error message.

```
WGB(config)#revocation-check none
```

Note: The `revocation-check none` command is necessary to avoid the problem described

in Cisco bug ID [CSCsl07349](#) ([registered](#) customers only) . WGB disassociates/reassociates often and takes a long time to reconnect.

```
WGB(config)#rsa keypair manual-keys 1024
```

3. Install the CA cert on the WGB: Get a copy of the CA cert: Browse to the CA: <http://ip.of.CA.server/certsrv> Click **Download a CA certificate, certificate chain, or CRL**. Choose **Encoding method: Base 64**. Click **Download CA certificate**. Save the .cer file. Install the CA cert:

```
WGB(config)#crypto pki authenticate CUT-PASTE
Enter the base 64 encoded CA certificate.
```

End with a blank line or the word "quit" on a line by itself

Now, paste in the text from the .cer file downloaded in the previous step.

```
-----BEGIN CERTIFICATE-----
[ ... ]
-----END CERTIFICATE-----
```

```
quit
```

Certificate has the following attributes:

```
Fingerprint: 45EC6866 A66B4D8F 2E05960F BC5C1B76
```

```
% Do you accept this certificate? [yes/no]: yes
```

```
Trustpoint CA certificate accepted.
```

```
% Certificate successfully imported
```

4. Request and install the client certificate on the WGB: Generate the certificate request on the WGB:

```
WGB(config)#crypto pki enroll CUT-PASTE
% Start certificate enrollment ..
```

```
% The subject name in the certificate will include: CN=WGB
% Include the router serial number in the subject name? [yes/no]: no
% Include an IP address in the subject name? [no]: no
Display Certificate Request to terminal? [yes/no]: yes
Certificate Request follows:
```

```
MIIBjzCB+QIBADAvMQwwCgYDVQQDEwNXR0IxBzAdBgkqhkiG9w0BCQIWEFdhQI5j
Y2llld2lmaS5jb20wgZ8wDQYJKoZIhvcNAQEBBQADgY0AMIGJAoGBAMuyZ0Y/xI3O
6Pwch3qA/JoBobYcvKHlc0B0qvqPgCmZgNb8nsFDV8ZFQKb3ySdIx1qOGtrn/Yoh
2LHzRKi+AWQHFGAB2vkFD0SJD8A6+YD/GqEdXGoo/e0eqJ7LgFq0wpUQoYlPxsPn
QUck9ZDwd8EZNYdxU/jBtLG9MLX4gta9AgMBAAGgITAfBgkqhkiG9w0BCQ4xEjAQ
MA4GA1UdDwEB/wQEAwIFoDANBgkqhkiG9w0BAQQFAAOBgQAsCITtCKRtul6JmG4rz
cDROO1QdmNYDuwksWHRgSHDMjVvBmoqA2bKeNsTj+svuX5S/Q2cGbzC6OLN/ftQ7
fw+RcKKm8+SpaEnU3eYGs3HhY7W9L4MY4JkY8I89ah15/V82SoIAOfCJDy5BvBP6
hk7GAPbMYk9wJaNruVEvkYoLQ==
```

```
---End - This line not part of the certificate request---
```

```
Redisplay enrollment request? [yes/no]: no
WGB(config)#
```

Request the Client/User certificate to the CA with the output previously gathered. Use a PC with access to the CA and request the User certificate using this method: Browse to the CA: <http://ip.of.CA.server/certsrv> Choose the "Request a certificate" option. Choose the "advanced certificate request" option. Choose the "Submit a certificate request by using a base-64-encoded CMC or PKCS #10 files, or submit a renewal request by using a base-64-encoded

PKCS #7 file" option. Paste in the certificate request that IOS generated from the "crypto pki enroll" command previously used, and just submit the request. Finally, just download the certificate as "Base 64 encoded". **Note:** You need to make sure that the certificate was actually generated for the WGB, with the Subject having "WGB" (the username you provided to the WGB) as the CN. Install the user certificate on the WGB:

```
WGB(config)#crypto pki import CUT-PASTE certificate
Enter the base 64 encoded certificate.
End with a blank line or the word "quit" on a line by itself
```

Now, paste in the text from the .cer file downloaded in the previous step.

```
-----BEGIN CERTIFICATE-----
[ ... ]
-----END CERTIFICATE-----
```

```
% Router Certificate successfully imported
```

5. Verify the certifications from the WGB CLI:

```
WGB#show crypto pki certificates
Certificate
  Status: Available
  Certificate Serial Number: 1379B072000000000000C
  Certificate Usage: General Purpose
  Issuer:
    cn=AARONLAB
  Subject:
    Name: WGB
    cn=WGB
  CRL Distribution Points:
    http://wswin/CertEnroll/AARONLAB.crl
  Validity Date:
    start date: 11:33:09 MST Mar 3 2008
    end date: 11:43:09 MST Mar 3 2009
  Associated Trustpoints: COPY-PASTE
```

```
CA Certificate
  Status: Available
  Certificate Serial Number: 612683248DBA539B44B039BD51CD1D48
  Certificate Usage: Signature
  Issuer:
    cn=AARONLAB
  Subject:
    cn=AARONLAB
  CRL Distribution Points:
    http://wswin/CertEnroll/AARONLAB.crl
  Validity Date:
    start date: 16:34:48 MST Feb 28 2008
    end date: 16:41:25 MST Feb 28 2018
  Associated Trustpoints: COPY-PASTE
```

[Configure the WGB SSID, Supplicant and Radio as Needed](#)

Complete these steps:

1. Configure the SSID. This should match the SSID configured on the WLC in this previous [step](#):

```
dot11 ssid EAPTLS
  authentication network-eap eap_methods
  authentication key-management wpa version 1
  dot1x credentials EAPTLS
  dot1x eap profile EAPTLS
  infrastructure-ssid
```

2. Configure the EAP-TLS supplicant. The username must match the CN on the trustpoint and the username entry in ACS.

```
eap profile EAPTLS
  method tls
!
dot1x credentials EAPTLS
  username WGB
  pki-trustpoint CUT-PASTE
```

3. Configure the radio interface as needed. In this example, the 2.4 GHz radio (Dot11Radio0) is used.

```
interface Dot11Radio0
  encryption mode ciphers aes-ccm tkip
  ssid EAPTLS
!
  packet retries 128 drop-packet
  station-role workgroup-bridge
```

Note: With `packet retries 128 drop-packet`, the WGB remains associated to its root AP as long as it can, so this is a suitable configuration for an immobile WGB. For a WGB that is physically roaming, these configurations can be used, in order of increasingly aggressive roaming:

```
packet retries 128
```

Note: or

```
packet retries 128
```

```
mobile station period 5 threshold 82
```

(tune the mobile station command as needed for a specialized application)

[Configure Entries for a Passive Client \(If Necessary\)](#)

If one or more "passive clients" are behind the WGB, for example, wired devices that have static IP addresses and that do not continuously transmit unsolicited IP data, then special steps need to be taken in order to ensure that the WGB and the CUWN can find those clients. In this example, the client has an IP address of 10.0.47.66 and a MAC address of 0040.96b4.7e8f.

Complete these steps in order to use this method:

1. Configure a static bridge entry on the WGB for the client:

```
B(config)#bridge 1 address 0040.96b4.7e8f
forward fastethernet0
```

2. Configure a static MAC-to-IP address mapping on the WLC: Configure the WLAN in order to enable MAC filtering, AAA override, and not to require DHCP:

```
(Cisco Controller) >show wlan summary
```

```
!--- Make a note of the WLAN ID for the SSID used for EAP-TLS. (Cisco Controller) >config
wlan disable 6
```

```
(Cisco Controller) >config wlan mac-filtering enable 6
```

```
(Cisco Controller) >config wlan aaa-override enable 6
```

```
(Cisco Controller) >config wlan dhcp_server 6 0.0.0.0
```

```
!--- Do not have DHCP required checked.
```

Add the MAC filter (MAC-to-IP mapping) for each client:

```
(Cisco Controller) >config macfilter add
```

```
0040.96b4.7e8f 6 management "client1" 10.0.47.66
```

[Special Notes if 802.11a \(5 GHz\) is Used](#)

Since 802.11a supports many more channels than 802.11b/g (2.4 GHz), it can take the WGB much longer to scan all available channels. Therefore, outages while you roam in 5 GHz, or after a connectivity problem to the root AP, can last for several seconds. Additionally, if you use DFS channels, channel scanning can take much longer, and brief outages after a DFS radar detection event can occur.

It is therefore recommended that if you use 802.11a, you should avoid the use of DFS channels, for example, in the FCC domain, and to use only the UNII-1 and UNII-3 bands. The Dot11Radio1 interface of the WGB should also be configured to scan only the channels in use in the coverage area. For example:

```
WGB(config-if)#mobile station scan
 36 40 44 48 149 153 157
```

Configurations

Here is an example WGB configuration for an AP1242, that uses Cisco IOS Software Release 12.4(10b)JA2, EAP-TLS authentication with WPA1-TKIP, 2.4 GHz.

Note: Some lines of this configuration have been moved to the second line due to space constraints.

```
version 12.4
no service pad
service timestamps debug datetime msec
service timestamps log datetime msec
no service password-encryption
!
hostname WGB
!
logging buffered 200000 debugging
enable secret 5 $1$xPtX$hjxzdWVR9qa4ykoxLYba91
!
no aaa new-model
clock timezone MST -7
!
!
!
dot11 ssid EAPTLS
 authentication network-eap eap_methods
 authentication key-management wpa version 1
 dot1x credentials EAPTLS
 dot1x eap profile EAPTLS
 infrastructure-ssid
!
power inline negotiation prestandard source
eap profile EAPTLS
 method tls
!
!
crypto pki trustpoint COPY-PASTE
 enrollment terminal
 subject-name CN=WGB
 revocation-check none
 rsa-keypair manual-keys 1024
```

```
!  
!  
crypto pki certificate chain COPY-PASTE  
  certificate 1379B07200000000000C  
[...]  
  quit  
  certificate ca 612683248DBA539B44B039BD51CD1D48  
[...]  
  quit  
dot1x credentials EAPTLS  
  username WGB  
  pki-trustpoint COPY-PASTE  
!  
username Cisco password 0 Cisco  
!  
bridge irb  
!  
!  
interface Dot11Radio0  
  no ip address  
  no ip route-cache  
  !  
  encryption mode ciphers tkip  
  !  
  ssid EAPTLS  
  !  
  packet retries 128 drop-packet  
  station-role workgroup-bridge  
  no dot11 qos mode  
  bridge-group 1  
  bridge-group 1 spanning-disabled  
!  
interface Dot11Radio1  
  no ip address  
  no ip route-cache  
  shutdown  
  !  
  station-role root  
  bridge-group 1  
  bridge-group 1 subscriber-loop-control  
  bridge-group 1 block-unknown-source  
  no bridge-group 1 source-learning  
  no bridge-group 1 unicast-flooding  
  bridge-group 1 spanning-disabled  
!  
interface FastEthernet0  
  no ip address  
  no ip route-cache  
  duplex auto  
  speed auto  
  bridge-group 1  
  bridge-group 1 spanning-disabled  
!  
interface BVI1  
  ip address dhcp client-id FastEthernet0  
  no ip route-cache  
  !  
  ip http server  
  no ip http secure-server  
  ip http help-path  
  
bridge 1 route ip  
!  
!
```

```
!  
line con 0  
line vty 0 4  
  login local  
!  
ntp server 10.0.47.1  
end
```

[Synchronize the Cisco IOS supplicant's clock and save its time to NVRAM \(for systems with Cisco IOS Software Release 12.4\(21a\)JY\)](#)

A Cisco IOS device whose supplicant is configured to perform certificate-based authentication of its network connection, which device is hereafter referred to as *the Supplicant*, may be unable to connect to the network, unless these steps are taken.

In order to make sure that the Supplicant, after a reload but before it has connected to the network, knows approximately what time it is, so that it can validate the certificate of the server, you must configure the Supplicant to learn the time from an NTP server, and to write the time to its NVRAM. This is a requirement for any system that runs Cisco IOS Software Release 12.4(21a)JY.

Complete these steps:

1. Configure the Supplicant to synchronize its time to a known good NTP server, to which the Supplicant has network access, and to store its time into its NVRAM. **Example 1.1. (on a system with SNTP, and without a hardware calendar):**

```
Supp(config)#ntp server 10.0.47.1  
Supp(config)#clock save interval 8  
Supp(config)#end  
Supp#write memory
```

Example 1.2. (on a system with NTP, and with a hardware calendar):

```
Supp(config)#ntp server 10.0.47.1 iburst  
Supp(config)#ntp update-calendar  
Supp(config)#end  
Supp#write memory
```

2. Make sure that the Supplicant has network connectivity to the NTP server and has synchronized its time. **Example 2.1:**

```
Supp#show sntp  
SNTP server      Stratum   Version   Last Receive  
10.0.47.1        3         1         00:00:09     Synced
```

Example 2.2:

```
Supp#show ntp status  
Clock is synchronized, stratum 4, reference is 10.95.42.129  
[ ... ]
```

3. Make sure that the correct time is saved to the hardware calendar of the Supplicant if it has one, or to NVRAM if it does not. **Example 3.1. On a system with no hardware calendar:** Reload the Supplicant in order to make sure that the time is saved to NVRAM. After it reloads, verify that the time is approximately correct, even when the NTP server is unavailable:

```
Supp#show clock detail  
*08:24:30.103 -0700 Thu Apr 15 2010  
No time source
```

Example 3.2. On a system with hardware calendar: Write the current, correct time to the

hardware calendar:
Supp#clock update-calendar

Verify that the calendar is correct:
Supp#show calendar

Verify

Use this section to confirm that your configuration works properly.

The [Output Interpreter Tool](#) ([registered](#) customers only) (OIT) supports certain **show** commands. Use the OIT to view an analysis of **show** command output.

Verify the WGB connection.

On the WLC, the radio MAC address of the WGB should appear as an Associated client. For example:

```
(Cisco Controller) >show client summary

Number of Clients..... 5

MAC Address          AP Name              Status      WLAN/   Auth Protocol  Port Wired
                   Guest-Lan
-----
00:00:39:dd:4d:24 AP0019.e802.3034  Associated   6       Yes  N/A           4     No
00:0e:9b:cb:d3:9c AP0019.e802.3034  Associated   1       No   802.11b       4     No
00:16:6f:50:e1:25 AP0019.e802.3034  Probing     N/A     No   802.11b       4     No
00:19:56:b0:7e:b6 AP0019.e802.3034  Associated   6       Yes  802.11b       4     No
00:40:96:b4:7e:8f AP0019.e802.3034  Associated   6       Yes  N/A           4     No
Use "show client detail <MAC>" to see more information on the WGB:
(Cisco Controller) >show client detail 00:19:56:b0:7e:b6
Client MAC Address..... 00:19:56:b0:7e:b6
Client Username ..... WGB
AP MAC Address..... 00:19:a9:42:e4:10
Client State..... Associated
Workgroup Bridge..... 2 client(s)
Wireless LAN Id..... 6
BSSID..... 00:19:a9:42:e4:15
Channel..... 1
IP Address..... 10.0.47.23
```

On the WGB, you can use the **show dot11 associations** and **show dot11 associations all-clients** commands in order to see more detail about the association to the AP. Use the **ping w.x.y.z** command in order to ping the WGB's default gateway.

Verify the WGB's client connectivity.

On the WGB, you can use the **show bridge 1 fastethernet0** command in order to see addresses learned through the FastEthernet0 interface:

```
WGB.Cisco.COM#show bridge 1 fastethernet0
```

Total of 300 station blocks, 292 free
Codes: P - permanent, S - self

Bridge Group 1:

Address	Action	Interface	Age	RX count	TX count
0000.39dd.4d24	forward	FastEthernet0	1	328	71
0040.96b4.7e8f	forward	FastEthernet0	P	0	352

On the WLC, the WGB's wired clients will show up as associated clients with protocol "N/A":

(Cisco Controller) >**show client summary**

Number of Clients..... 5

MAC Address	AP Name	Status	WLAN/ Guest-Lan	Auth	Protocol	Port	Wired
00:00:39:dd:4d:24	AP0019.e802.3034	Associated		Yes	N/A	4	No
00:0e:9b:cb:d3:9c	AP0019.e802.3034	Associated	1	No	802.11b	4	No
00:16:6f:50:e1:25	AP0019.e802.3034	Probing	N/A	No	802.11b	4	No
00:19:56:b0:7e:b6	AP0019.e802.3034	Associated	6	Yes	802.11b	4	No
00:40:96:b4:7e:8f	AP0019.e802.3034	Associated	6	Yes	N/A	4	No

(Cisco Controller) >show client detail 00:00:39:dd:4d:24

Client MAC Address..... 00:00:39:dd:4d:24
Client Username N/A
AP MAC Address..... 00:19:a9:42:e4:10
Client State..... Associated
Workgroup Bridge Client..... WGB: 00:19:56:b0:7e:b6
Wireless LAN Id..... 6
BSSID..... 00:19:a9:42:e4:15
Channel..... 1

[Troubleshoot](#)

This section provides information you can use to troubleshoot your configuration.

[Troubleshooting Commands](#)

The [Output Interpreter Tool](#) ([registered](#) customers only) (OIT) supports certain **show** commands. Use the OIT to view an analysis of **show** command output.

Note: Refer to [Important Information on Debug Commands](#) before you use **debug** commands.

[Debugging Examples](#)

- [WGB-side example](#)
- [WLC-side example](#)

[WGB-side example](#)

On the WGB, this example assumes 2.4 GHz; if you use 5 GHz, specify `Dot11Radio1` instead of `Dot11Radio0`.

```

WGB#no debug dot11 dot11radio0 print printf
!--- This runs the radio debugs through !--- the standard Cisco IOS logger. WGB#debug
dot11 dot11radio0 trace print mgmt uplink
!--- radio driver debugs: 802.11 management frames !--- and uplink events WGB#debug
dot11 supp-sm-dot1x
!--- interface to the 802.1X supplicant

```

Here is an example of a normal association given in the previous configuration:

WGB-side Example

```

Mar  4 23:22:39.427: 108DD0BF-0 Uplink: Enabling active
scan
Mar  4 23:22:39.427: 108DD0D0-0 Uplink: Not busy, scan
all channels
Mar  4 23:22:39.427: 108DD0DE-0 Uplink: Scanning
Mar  4 23:22:39.430: 108DDF83-0 Uplink: Rcvd response
from 0019.a942.e415
                                channel 1 3237
!--- WGB scans the 2.4 GHz channels, !--- found an AP on
channel 1. Mar  4 23:22:39.470: 108E7B31-0 Uplink:
dot11_uplink_scan_done: ssid_accept returns 0x0
key_mgmt 0x50F201 encrypt_type 0x20 Mar  4 23:22:39.470:
108E7B67-0 Uplink: ssid EAPTLS auth leap Mar  4
23:22:39.471: 108E7B77-0 Uplink: try 0019.a942.e415, enc
20 key 1, priv 1, eap 11 Mar  4 23:22:39.471: 108E7B93-0
Uplink: Authenticating Mar  4 23:22:39.479: 108E9C71 t 1
0 - B000 13A 42E415 B07EB6 42E415 D9E0 auth 1 6
algorithm 128 sequence 1 status 0 Mar  4 23:22:39.480:
108EA160 r 1 73/ 26- B000 13A B07EB6 42E415 42E415 5E70
auth 1 37 algorithm 128 sequence 2 status 0 221 - 0 40
96 C 1 A 22 79 95 1A 7C 18 1 0 0 CA 4 0 0 0 0 74 52 EA
31 F4 9E 89 5A !--- WGB completes 802.11 authentication.
Mar  4 23:22:39.480: 108EA1EB-0 Uplink: Associating Mar  4
23:22:39.481: 108EA951 t 1 0 - 0000 13A 42E415 B07EB6
42E415 D9F0 assreq 1 119 cap 431 infra privacy shorthdr
listen interval 200 ssid EAPTLS rates 82 84 8B C 12 96
18 24 extrates 30 48 60 6C aironet WGB.Cisco.COM load 0
clients 0 hops 0 device 7C-2700 refresh 15 CW 0-0 flags
0 distance 0 ccxver 5 221 - 0 40 96 14 0 IP 10.0.47.23 1
wpa1 mcst tkip ucst tkip keymgmt wpa cap 2800 221 - 0 40
96 6 2 Mar  4 23:22:39.484: 108EB2C6 r 1 80/77 19- 1000
13A B07EB6 42E415 42E415 5E80 assrsp 1 101 cap 31 infra
privacy shorthdr status 0 aid C003 rates 82 4 B 16
aironet AP0019.e802.303 load 0 clients 0 hops 0 device
8F-2700 refresh 15 CW 31-1023 flags 40 distance 0 IP
10.0.47.6 0 ccxver 5 221 - 0 40 96 14 0 221 - 0 40 96 C
1 A 22 7E 95 1A 7C 18 1 0 0 CB 4 0 0 0 0 FB 4C F3 7D D
29 71 E2 !--- WGB completes 802.11 association. Mar  4
23:22:39.486: Uplink address set to 0019.a942.e415 Mar  4
23:22:39.486: Initialising common IOS structures for
dot1x Mar  4 23:22:39.486: Done. Mar  4 23:22:39.486:
DOT1X_SHIM: Start supplicant on Dot11Radio0 (credentials
EAPTLS) Mar  4 23:22:39.486: DOT1X_SHIM: Starting
dot1x_mgr_auth (auth type 128) Mar  4 23:22:39.486:
DOT1X_SHIM: Initialising WPA [or WPA-PSK or CCKM] key
management module !--- Starting the EAP-TLS supplicant
Mar  4 23:22:39.488: DOT1X_SHIM: Dot1x pkt sent (uplink)
with dest 0019.a942.e415 Mar  4 23:22:39.489: DOT1X_SHIM:
No AAA client found for 0019.a942.e415 (on Dot11Radio0)

```

```
Mar 4 23:22:39.489: DOT1X_SHIM: Dot1x pkt sent (uplink)
with dest 0019.a942.e415 Mar 4 23:22:39.490: DOT1X_SHIM:
No AAA client found for 0019.a942.e415 (on Dot11Radio0)
!--- The "No AAA client found" message appears !--- to
be a bogon and can be ignored. Mar 4 23:22:39.491:
DOT1X_SHIM: Dot1x pkt sent (uplink) with dest
0019.a942.e415 Mar 4 23:22:39.491: 108EB9B4-0 Uplink:
EAP authenticating Mar 4 23:22:39.491: 108EBD22 r 11 73/
4 - 0802 13A B07EB6 42E415 42E415 5E90 164 0100 0034
0101 0034 0100 6E65 7477 6F72 6B69 643D 4541 5054 4C53
2C6E 6173 6964 3D74 7563 736F 6E2D 776C 6332 3030 362C
706F 7274 6964 3D34 0000 Mar 4 23:22:39.492: 108EC770 t
11 0 - 0801 13A 42E415 B07EB6 42E415 DA00 168 EAPOL2
EAPOL start Mar 4 23:22:39.492: 108ECA4D r 11 74/ 18-
0802 13A B07EB6 42E415 42E415 5EA0 164 0100 0034 0102
0034 0100 6E65 7477 6F72 6B69 643D 4541 5054 4C53 2C6E
6173 6964 3D74 7563 736F 6E2D 776C 6332 3030 362C 706F
7274 6964 3D34 0000 Mar 4 23:22:39.492: 108ECDE2 t 11 0
- 0801 13A 42E415 B07EB6 42E415 DA10 168 EAPOL2 EAP id 1
resp ident "WGB" Mar 4 23:22:39.493: 108ED000 t 11 0 -
0801 13A 42E415 B07EB6 42E415 DA20 168 EAPOL2 EAP id 2
resp ident "WGB" Mar 4 23:22:39.524: 108F50C4 r 11 74/
18- 080A 13A B07EB6 42E415 42E415 5EC0 131 0100 0013
01AF 0013 1101 0008 E23F 829E AE45 57EB 5747 4200 0000
0000 0000 00 !--- The WGB sends an EAPOL START, !--- the
WLC authenticator sends an EAP ID Request, !--- and the
WGB responds with an EAP ID response. Mar 4
23:22:39.525: DOT1X_SHIM: No AAA client found for
0019.a942.e415 (on Dot11Radio0) Mar 4 23:22:39.525:
DOT1X_SHIM: Dot1x pkt sent (uplink) with dest
0019.a942.e415 Mar 4 23:22:39.526: 108F57D0 t 11 0 -
0801 13A 42E415 B07EB6 42E415 DA30 168 EAPOL2 EAP id 175
resp nak 0D Mar 4 23:22:39.547: 108FA89C r 11 86/77 19-
080A 13A B07EB6 42E415 42E415 5ED0 118 0100 0006 01B0
0006 0D20 0000 0000 0000 0000 Mar 4 23:22:39.547:
DOT1X_SHIM: No AAA client found for 0019.a942.e415 (on
Dot11Radio0) Mar 4 23:22:39.561: DOT1X_SHIM: Dot1x pkt
sent (uplink) with dest 0019.a942.e415 Mar 4
23:22:39.561: 108FE059 t 11 0 - 0801 13A 42E415 B07EB6
42E415 DA40 186 EAPOL2 EAP id 176 resp tls 8000 0000
3216 0301 002D 0100 0029 0301 47CD D9BF CE1B 71B1 A815
CB99 8C80 8876 39F2 57A3 0F02 F382 147E 9D0C 657E 3AA7
Mar 4 23:22:39.572: DOT1X_SHIM: No AAA client found for
0019.a942.e415 (on Dot11Radio0) Mar 4 23:22:39.573:
DOT1X_SHIM: Dot1x pkt sent (uplink) with dest
0019.a942.e415 Mar 4 23:22:39.573: 10900868 r 11 86/77
20- 0802 13A B07EB6 42E415 42E415 5EF0 11024 0100 03F4
01B1 03F4 0DC0 0000 079D 1603 0100 4A02 0000 4603 0147
CDD9 B413 0683 9734 4D26 136F EC8F ECD3 5D3B 77C7 4D20
7DA1 9B17 D7D3 E4A6 1720 Mar 4 23:22:39.574: 109012E6 t
11 1 - 0809 13A 42E415 B07EB6 42E415 DA50 168 EAPOL2 EAP
id 177 resp tls 00 Mar 4 23:22:39.582: DOT1X_SHIM: No
AAA client found for 0019.a942.e415 (on Dot11Radio0) Mar
4 23:22:39.734: DOT1X_SHIM: Dot1x pkt sent (uplink) with
dest 0019.a942.e415 Mar 4 23:22:39.735: 1090317E r 11
/78 19- 0802 13A B07EB6 42E415 42E415 5F00 1965 0100
03B9 01B2 03B9 0D00 C687 1DB6 065B 2467 2609 EE5F 9C64
F3A9 C199 493E 2B79 F157 1765 6C2F C409 4D54 7DA4 6791
4859 ECAA 685B 0F66 C5E9 22A6 Mar 4 23:22:39.736:
10928A31 t 11 0 - 0801 13A 42E415 B07EB6 42E415 DA60
11239 EAPOL2 EAP id 178 resp tls 8000 0004 B316 0301
036D 0B00 0369 0003 6600 0363 3082 035F 3082 0247 A003
0201 0202 0A13 79B0 7200 0000 0000 0C30 0D06 Mar 4
23:22:39.755: 1092D464 r 11 /78 18- 0802 13A B07EB6
```

```
42E415 42E415 5F40 165 0100 0035 01B3 0035 0D80 0000
002B 1403 0100 0101 1603 0100 20B8 EBFA 2DDB 2E1A BF84
37A8 892C 84C5 50B2 B1A5 6F3E B2B5 981A 2899 1DE2 B470
6800 Mar 4 23:22:39.755: DOT1X_SHIM: No AAA client found
for 0019.a942.e415 (on Dot11Radio0) Mar 4 23:22:39.760:
DOT1X_SHIM: Dot1x pkt sent (uplink) with dest
0019.a942.e415 Mar 4 23:22:39.760: 1092E92C t 11 0 -
0801 13A 42E415 B07EB6 42E415 DA70 168 EAPOL2 EAP id 179
resp tls 00 Mar 4 23:22:39.770: 10930F50 r 11 75/80 19-
0802 13A B07EB6 42E415 42E415 5F60 116 0100 0004 03B3
0004 0000 0000 0000 0000 Mar 4 23:22:39.770: DOT1X_SHIM:
No AAA client found for 0019.a942.e415 (on Dot11Radio0)
Mar 4 23:22:39.774: DOT1X_SHIM: Received Dot1x success -
Authenticated with EAP-TLS !--- EAP-TLS authentication
is successful, !--- now come the keys. Mar 4
23:22:39.774: DOT1X_SHIM: treat key material as wpa-v1
v2 pmk Mar 4 23:22:39.774: DOT1X_SHIM: WPA PMK key size
truncated from 64 to 32 Mar 4 23:22:39.777: DOT1X_SHIM:
Got Eapol key packet from dot1x manager Mar 4
23:22:39.777: DOT1X_SHIM: Passing key packet to KM
module Mar 4 23:22:39.777: supp_km_processKey:
descriptor type = 254 Mar 4 23:22:39.777:
supp_km_processKey: key length = 137 Mar 4 23:22:39.778:
109319B7 r 11 /77 16- 080A 13A B07EB6 42E415 42E415 5F70
1107 0103 005F FE00 8900 2000 0000 0000 0000 006E 64D0
C659 1C91 11D2 6040 C251 0592 E6B6 3799 0EDE B1BD B3A6
87B7 8C9B 0D5E DF00 0000 0000 0000 0000 Mar 4
23:22:39.779: 109332C2 t 11 1 - 0809 13A 42E415 B07EB6
42E415 DA80 1133 EAPOL key desc FE info 109 len 20
replay 0000000000000000 nonce
11AADA303F5F9B2357A932B3093483905E69F8408D019FB2EF56F7AD
706F0759 iv 00000000000000000000000000000000 rsc
0000000000000000 id 0000000000000000 mic
DBD06C383B83E3478F802844095E9444 datalen 1A key DD18
0050 F201 0100 0050 F202 0100 0050 F202 0100 0050 F201
2800 Mar 4 23:22:39.780: 109336C1 r 11 83/78 18- 0802
13A B07EB6 42E415 42E415 5F80 1133 0103 0079 FE01 C900
2000 0000 0000 0000 016E 64D0 C659 1C91 11D2 6040 C251
0592 E6B6 3799 0EDE B1BD B3A6 87B7 8C9B 0D5E DF6E 64D0
C659 1C91 11D2 Mar 4 23:22:39.781: DOT1X_SHIM: Got Eapol
key packet from dot1x manager Mar 4 23:22:39.781:
DOT1X_SHIM: Passing key packet to KM module Mar 4
23:22:39.781: supp_km_processKey: descriptor type = 254
Mar 4 23:22:39.781: supp_km_processKey: key length = 457
Mar 4 23:22:39.781: dot1x_pakio_plumb_keys: trying to
plumb PTK key Mar 4 23:22:39.782: 10933E11 t 11 0 - 0801
13A 42E415 B07EB6 42E415 DA90 1107 EAPOL key desc FE
info 109 len 20 replay 0000000000000001 nonce
00000000000000000000000000000000000000000000000000000000
00000000 iv 00000000000000000000000000000000 rsc
0000000000000000 id 0000000000000000 mic
3A59680D1130EC24B00F7246F9D0738F datalen 0 key Mar 4
23:22:39.785: 10934749 r 11 88/77 17- 0842 13A B07EB6
42E415 42E415 5F90 1155 IV 0103007F-FE039100 2000 0000
0000 0000 026E 64D0 C659 1C91 11D2 6040 C251 0592 E6B6
3799 0EDE B1BD B3A6 87B7 8C9B 0D5E D76E 64D0 C659 1C91
11D2 Mar 4 23:22:39.785: DOT1X_SHIM: Got Eapol key
packet from dot1x manager Mar 4 23:22:39.785:
DOT1X_SHIM: Passing key packet to KM module Mar 4
23:22:39.785: supp_km_processKey: descriptor type = 254
Mar 4 23:22:39.785: supp_km_processKey: key length = 913
Mar 4 23:22:39.786: dot1x_pakio_plumb_keys: trying to
plumb vlan key - length: 32 Mar 4 23:22:39.787: %DOT11-
4-UPLINK_ESTABLISHED: Interface Dot11Radio0, Associated
```



```
To AP AP0019.e802.303 0019.a942.e415 [EAP-TLS WPA] Mar 4
23:22:39.787: %LINK-3-UPDOWN: Interface Dot11Radio0,
changed state to up Mar 4 23:22:39.789: 10934D63-0
Uplink: Done Mar 4 23:22:39.789: 10934D94-0 Interface up
Mar 4 23:22:39.790: 10934ED7 t 11 0 - 0841 13A 42E415
B07EB6 42E415 DAA0 1115 EAPOL key desc FE info 311 len 0
replay 0000000000000002 nonce
0000000000000000000000000000000000000000000000000000000000000000
00000000 iv 0000000000000000000000000000000000000000000000000000
0000000000000000 id 0000000000000000 mic
DA60CCDAE27E7362B9B720B52715E081 datalen 0 key !--- The
keys are all distributed, !--- and the Dot11Radio0
interface is fully up.
```

WLC-side Debugs

WLC-side Example

```
(Cisco Controller) >debug mac addr
00:19:56:b0:7e:b6

!--- Filter debugs on the radio !--- MAC address of the
WGB. (Cisco Controller) >debug dot11 state enable

(Cisco Controller) >debug dot1x events enable

(Cisco Controller) >debug dot1x states enable

(Cisco Controller) >debug pem events enable

(Cisco Controller) >debug pem state enable

(Cisco Controller) >debug aaa packet enable

(Cisco Controller) >debug aaa events enable

(Cisco Controller) >debug aaa events enable

Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6 Processing
WPA IE type 221,
length 24 for mobile
00:19:56:b0:7e:b6
Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6 10.0.47.23
RUN (20)
Change state to START (0) last
state RUN (20)
Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6 10.0.47.23
START (0)
Initializing policy
Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6 10.0.47.23
START (0)
Change state to AUTHCHECK (2)
last state RUN (20)
Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6 10.0.47.23
AUTHCHECK (2)
Change state to 8021X_REQD (3)
last state RUN (20)
Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6 10.0.47.23
8021X_REQD (3)
Plumbed mobile LWAPP rule on
AP 00:19:a9:42:e4:10
```

```
Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6
apfPemAddUser2 (apf_policy.c:209)
    Changing state for mobile
00:19:56:b0:7e:b6 on
    AP 00:19:a9:42:e4:10 from Associated to Associated
Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6
apfProcessAssocReq (apf_80211.c:4149)
    Changing state for mobile
00:19:56:b0:7e:b6 on
    AP 00:19:a9:42:e4:10 from Associated to Associated

!--- WGB is associated in 802.11. !--- Note in this case
that the WGB associated !--- when it was already
associated. Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6
dot1x - moving mobile 00:19:56:b0:7e:b6 into Connecting
state Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6 Sending
EAP-Request/Identity to mobile 00:19:56:b0:7e:b6 (EAP Id
1) Tue Mar 4 16:45:56 2008: 00:19:56:b0:7e:b6 10.0.47.23
Removed NPU entry. Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 Received EAPOL START from mobile
00:19:56:b0:7e:b6 Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 dot1x - moving mobile
00:19:56:b0:7e:b6 into Connecting state Tue Mar 4
16:45:59 2008: 00:19:56:b0:7e:b6 Sending EAP-
Request/Identity to mobile 00:19:56:b0:7e:b6 (EAP Id 2)
Tue Mar 4 16:45:59 2008: 00:19:56:b0:7e:b6 Received
EAPOL EAPPKT from mobile 00:19:56:b0:7e:b6 Tue Mar 4
16:45:59 2008: 00:19:56:b0:7e:b6 Received EAP Response
packet with mismatching id (currentid=2, eapid=1) from
mobile 00:19:56:b0:7e:b6 Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 Received EAPOL EAPPKT from mobile
00:19:56:b0:7e:b6 Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 Received Identity Response (count=2)
from mobile 00:19:56:b0:7e:b6 !--- WGB sends EAPOL START
while !--- WLC sends its EAP ID-request, !--- which
confuses the state machines for a moment, !--- but
eventually we get on track, and the WLC !--- gets its
ID-response from the WGB supplicant. Tue Mar 4 16:45:59
2008: 00:19:56:b0:7e:b6 EAP State update from Connecting
to Authenticating for mobile 00:19:56:b0:7e:b6 Tue Mar 4
16:45:59 2008: 00:19:56:b0:7e:b6 dot1x - moving mobile
00:19:56:b0:7e:b6 into Authenticating state Tue Mar 4
16:45:59 2008: 00:19:56:b0:7e:b6 Entering Backend Auth
Response state for mobile 00:19:56:b0:7e:b6 Tue Mar 4
16:45:59 2008: 00:19:56:b0:7e:b6 Successful transmission
of Authentication Packet (id 17) to 10.0.47.42:1812,
proxy state 00:19:56:b0:7e:b6-00:00 Tue Mar 4 16:45:59
2008: 00000000: 01 11 00 9c 85 82 35 15 62 0f 50 bd 32
60 0c e6 .....5.b.P.2`.. Tue Mar 4 16:45:59 2008:
00000010: de 94 b2 40 01 05 57 47 42 1f 13 30 30 2d 31
39 ...@..WGB..00-19 Tue Mar 4 16:45:59 2008: 00000020:
2d 35 36 2d 42 30 2d 37 45 2d 42 36 1e 1a 30 30 -56-B0-
7E-B6..00 Tue Mar 4 16:45:59 2008: 00000030: 2d 31 39 2d
41 39 2d 34 32 2d 45 34 2d 31 30 3a -19-A9-42-E4-10: Tue
Mar 4 16:45:59 2008: 00000040: 45 41 50 54 4c 53 05 06
00 00 00 04 04 06 0a 00 EAPTLS..... Tue Mar 4
16:45:59 2008: 00000050: 2f 06 20 10 74 75 63 73 6f 6e
2d 77 6c 63 32 30 /...tucson-wlc20 Tue Mar 4 16:45:59
2008: 00000060: 30 36 1a 0c 00 00 37 63 01 06 00 00 00
06 06 06 06....7c..... Tue Mar 4 16:45:59 2008:
00000070: 00 00 00 02 0c 06 00 00 05 14 3d 06 00 00 00
13 .....=..... Tue Mar 4 16:45:59 2008: 00000080:
4f 0a 02 02 00 08 01 57 47 42 50 12 c5 f3 f5 9c
O.....WGBP.... Tue Mar 4 16:45:59 2008: 00000090: c0
```

```
81 0e 3e 23 c0 a7 1b 03 f7 af 5b ...>#.....[ Tue Mar 4
16:45:59 2008: 00000000: 0b 11 00 47 54 d3 b6 45 75 eb
83 b7 97 7c 80 1b ...GT..Eu....|.. Tue Mar 4 16:45:59
2008: 00000010: 13 03 71 1d 4f 15 01 b0 00 13 11 01 00
08 3d 17 ..q.O.....=. Tue Mar 4 16:45:59 2008:
00000020: 4a 94 eb c7 3b 3e 57 47 42 18 0c 53 56 43 3d
30 J...;>WGB..SVC=0 Tue Mar 4 16:45:59 2008: 00000030:
2e 36 34 37 3b 50 12 67 50 d3 ad 88 7d 16 8b 5b
.647;P.gP...)}..[ Tue Mar 4 16:45:59 2008: 00000040: d1
25 57 56 b2 ec 76.%WV..v Tue Mar 4 16:45:59 2008:
****Enter processIncomingMessages: response code=11 Tue
Mar 4 16:45:59 2008: ****Enter processRadiusResponse:
response code=11 Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 Access-Challenge received from RADIUS
server 10.0.47.42 for mobile 00:19:56:b0:7e:b6 receiveId
= 7 Tue Mar 4 16:45:59 2008: 00:19:56:b0:7e:b6
Processing Access-Challenge for mobile 00:19:56:b0:7e:b6
!--- The WLC forwards the ID-request info, !--- that it
had received !--- in 802.1X from the WGB supplicant, to
the RADIUS server, !--- in a RADIUS Access-Request
packet. !--- The RADIUS server responds with an Access-
Challenge. !--- If there is a configuration problem with
RADIUS, then either !--- the RADIUS server does not
respond, or it responds !--- with a RADIUS Access-
Reject. !--- If EAP-TLS goes well, there is much back
and forth !--- between the EAP exchange on the wireless
!--- link, and the RADIUS exchange between the WLC and
ACS. Tue Mar 4 16:45:59 2008: 00:19:56:b0:7e:b6 Entering
Backend Auth Req state (id=176) for mobile
00:19:56:b0:7e:b6 Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 WARNING: updated EAP-Identifer 2 ==>
176 for STA 00:19:56:b0:7e:b6 Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 Sending EAP Request from AAA to mobile
00:19:56:b0:7e:b6 (EAP Id 176) Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 Received EAPOL EAPPKT from mobile
00:19:56:b0:7e:b6 Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 Received EAP Response from mobile
00:19:56:b0:7e:b6 (EAP Id 176, EAP Type 3) Tue Mar 4
16:45:59 2008: 00:19:56:b0:7e:b6 Entering Backend Auth
Response state for mobile 00:19:56:b0:7e:b6 Tue Mar 4
16:45:59 2008: 00:19:56:b0:7e:b6 Successful transmission
of Authentication Packet (id 18) to 10.0.47.42:1812,
proxy state 00:19:56:b0:7e:b6-00:00 Tue Mar 4 16:45:59
2008: 00000000: 01 12 00 a6 d5 64 56 8a e8 27 fa de ca
69 c4 2a .....dV...'...i.* Tue Mar 4 16:45:59 2008:
00000010: cd 06 26 0c 01 05 57 47 42 1f 13 30 30 2d 31
39 ..&...WGB..00-19 Tue Mar 4 16:45:59 2008: 00000020:
2d 35 36 2d 42 30 2d 37 45 2d 42 36 1e 1a 30 30 -56-B0-
7E-B6..00 Tue Mar 4 16:45:59 2008: 00000030: 2d 31 39 2d
41 39 2d 34 32 2d 45 34 2d 31 30 3a -19-A9-42-E4-10: Tue
Mar 4 16:45:59 2008: 00000040: 45 41 50 54 4c 53 05 06
00 00 00 04 04 06 0a 00 EAPTLS..... Tue Mar 4
16:45:59 2008: 00000050: 2f 06 20 10 74 75 63 73 6f 6e
2d 77 6c 63 32 30 /...tucson-wlc20 Tue Mar 4 16:45:59
2008: 00000060: 30 36 1a 0c 00 00 37 63 01 06 00 00 00
06 06 06 06....7c..... Tue Mar 4 16:45:59 2008:
00000070: 00 00 00 02 0c 06 00 00 05 14 3d 06 00 00 00
13 .....=..... Tue Mar 4 16:45:59 2008: 00000080:
4f 08 02 b0 00 06 03 0d 18 0c 53 56 43 3d 30 2e
O.....SVC=0. Tue Mar 4 16:45:59 2008: 00000090: 36
34 37 3b 50 12 43 6e 32 b6 e9 11 a3 47 8e 96
647;P.Cn2....G.. Tue Mar 4 16:45:59 2008: 000000a0: dc
f0 37 a8 37 9e..7.7. Tue Mar 4 16:45:59 2008: 00000000:
0b 12 00 4b 71 7a 36 1d d9 24 16 8d c0 2f 45 52
```

```
...Kqz6..$/ER Tue Mar 4 16:45:59 2008: 00000010: 82
3d 58 cf 4f 08 01 b1 00 06 0d 20 18 1d 45 41
.=X.O.....EA Tue Mar 4 16:45:59 2008: 00000020: 50
3d 30 2e 32 30 32 2e 32 37 65 61 2e 31 3b 53
P=0.202.27ea.1;S Tue Mar 4 16:45:59 2008: 00000030: 56
43 3d 30 2e 36 34 37 3b 50 12 71 bf 1f 5c c7
VC=0.647;P.q..\ Tue Mar 4 16:45:59 2008: 00000040: 69
7e e8 cc 9d 71 18 de b7 e5 b7 i~...q..... Tue Mar 4
16:45:59 2008: ****Enter processIncomingMessages:
response code=11 Tue Mar 4 16:45:59 2008: ****Enter
processRadiusResponse: response code=11 Tue Mar 4
16:45:59 2008: 00:19:56:b0:7e:b6 Access-Challenge
received from RADIUS server 10.0.47.42 for mobile
00:19:56:b0:7e :b6 receiveId = 7 Tue Mar 4 16:45:59
2008: 00:19:56:b0:7e:b6 Processing Access-Challenge for
mobile 00:19:56:b0:7e:b6 Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 Entering Backend Auth Req state
(id=177) for mobile 00:19:56:b0:7e:b6 Tue Mar 4 16:45:59
2008: 00:19:56:b0:7e:b6 Sending EAP Request from AAA to
mobile 00:19:56:b0:7e:b6 (EAP Id 177) Tue Mar 4 16:45:59
2008: 00:19:56:b0:7e:b6 Received EAPOL EAPPKT from
mobile 00:19:56:b0:7e:b6 Tue Mar 4 16:45:59 2008:
00:19:56:b0:7e:b6 Received EAP Response from mobile
00:19:56:b0:7e:b6 (EAP Id 177, EAP Type 13) Tue Mar 4
16:45:59 2008: 00:19:56:b0:7e:b6 Entering Backend Auth
Response state for mobile 00:19:56:b0:7e:b6 Tue Mar 4
16:45:59 2008: 00:19:56:b0:7e:b6 Successful transmission
of Authentication Packet (id 19) to 10.0.47.42:1812,
proxy state 00:19:56:b0:7e:b6-00:00 Tue Mar 4 16:45:59
2008: 00000000: 01 13 00 ed 30 a2 b8 d3 6c 6a e9 08 04
f9 b9 32 ...0...lj.....2 Tue Mar 4 16:45:59 2008:
00000010: 98 fe 36 62 01 05 57 47 42 1f 13 30 30 2d 31
39 ..6b..WGB..00-19 Tue Mar 4 16:45:59 2008: 00000020:
2d 35 36 2d 42 30 2d 37 45 2d 42 36 1e 1a 30 30 -56-B0-
7E-B6..00 Tue Mar 4 16:45:59 2008: 00000030: 2d 31 39 2d
41 39 2d 34 32 2d 45 34 2d 31 30 3a -19-A9-42-E4-10: Tue
Mar 4 16:45:59 2008: 00000040: 45 41 50 54 4c 53 05 06
00 00 00 04 04 06 0a 00 EAPTLS..... Tue Mar 4
16:45:59 2008: 00000050: 2f 06 20 10 74 75 63 73 6f 6e
2d 77 6c 63 32 30 /...tucson-wlc20 Tue Mar 4 16:45:59
2008: 00000060: 30 36 1a 0c 00 00 37 63 01 06 00 00 00
06 06 06 06....7c..... Tue Mar 4 16:45:59 2008:
00000070: 00 00 00 02 0c 06 00 00 05 14 3d 06 00 00 00
13 .....=..... Tue Mar 4 16:45:59 2008: 00000080:
4f 3e 02 b1 00 3c 0d 80 00 00 00 32 16 03 01 00
O>...<.....2.... Tue Mar 4 16:45:59 2008: 00000090: 2d
01 00 00 29 03 01 47 cd df 36 c4 bc 40 48 75 -
...)..G..6..@Hu Tue Mar 4 16:45:59 2008: 000000a0: f4 09
ea 60 0c 40 fc 99 a0 e7 11 15 00 7e ca 90
...`.@.....~.. Tue Mar 4 16:45:59 2008: 000000b0: da
5a d3 39 45 be ca 00 00 02 00 04 01 00 18 1d
.Z.9E..... Tue Mar 4 16:45:59 2008: 000000c0: 45
41 50 3d 30 2e 32 30 32 2e 32 37 65 61 2e 31
EAP=0.202.27ea.1 Tue Mar 4 16:45:59 2008: 000000d0: 3b
53 56 43 3d 30 2e 36 34 37 3b 50 12 c0 6b 4c
;SVC=0.647;P..kL Tue Mar 4 16:45:59 2008: 000000e0: 37
6c 1a 4f 58 89 18 2b c4 0e 99 cd 0f 71.OX..+..... Tue
Mar 4 16:45:59 2008: 00000000: 0b 13 04 3f 5d 80 89 e2
e7 3f b0 c4 4c 99 d2 bd ...?].....?.L... Tue Mar 4
16:45:59 2008: 00000010: e5 e3 6e af 4f ff 01 b2 03 f4
0d c0 00 00 07 9d ..n.O..... Tue Mar 4 16:45:59
2008: 00000020: 16 03 01 00 4a 02 00 00 46 03 01 47 cd
df 2a f3 ...J...F..G..*. Tue Mar 4 16:45:59 2008:
00000030: 19 0f 6f 52 2f a7 c3 00 d4 c8 f0 50 1c 8f 47
```

f4 ..oR/.....P..G. Tue Mar 4 16:45:59 2008: 00000040:
97 1b f2 a0 ca a9 f4 27 0c 34 32 20 d9 33 c4 27
.....'.42..3.' Tue Mar 4 16:45:59 2008: 00000050: 81
91 e4 97 d7 a6 6b 03 58 1a 4a c8 6d 4a e7 ef
.....k.X.J.mJ.. Tue Mar 4 16:45:59 2008: 00000060: 9d
f8 fd ad c9 95 aa b5 3e f5 1b dc 00 04 00 16
.....>..... Tue Mar 4 16:45:59 2008: 00000070: 03
01 07 37 0b 00 07 33 00 07 30 00 03 c2 30 82
...7...3..0...0. Tue Mar 4 16:45:59 2008: 00000080: 03
be 30 82 02 a6 a0 03 02 01 02 02 0a 61 0f c8
..0.....a.. Tue Mar 4 16:45:59 2008: 00000090: d9
00 00 00 00 00 02 30 0d 06 09 2a 86 48 86 f7
.....0...*.H.. Tue Mar 4 16:45:59 2008: 000000a0: 0d
01 01 05 05 00 30 13 31 11 30 0f 06 03 55 04
.....0.1.0...U. Tue Mar 4 16:45:59 2008: 000000b0: 03
13 08 41 41 52 4f 4e 4c 41 42 30 1e 17 0d 30
...AARONLAB0...0 Tue Mar 4 16:45:59 2008: 000000c0: 38
30 32 32 39 30 30 30 32 35 30 5a 17 0d 30 39
80229000250Z..09 Tue Mar 4 16:45:59 2008: 000000d0: 30
32 32 38 30 30 31 32 35 30 5a 30 12 31 10 30
0228001250Z0.1.0 Tue Mar 4 16:45:59 2008: 000000e0: 0e
06 03 55 04 03 13 07 41 43 53 63 65 72 74 30
...U....ACScert0 Tue Mar 4 16:45:59 2008: 000000f0: 81
9f 30 0d 06 09 2a 86 48 86 f7 0d 01 01 01 05
..0...*.H..... Tue Mar 4 16:45:59 2008: 00000100: 00
03 81 8d 00 30 81 89 02 81 81 00 e4 cb 25 a1
.....0.....%. Tue Mar 4 16:45:59 2008: 00000110: 96
3f df 4f ff 0d de 8a 89 6f 33 b1 b3 b9 fe 6e
?.O.....o3....n Tue Mar 4 16:45:59 2008: 00000120: df
6a 01 cf 7f b4 44 5b 6b 4e 91 17 9c 88 d3 6c
.j....D[kN.....l Tue Mar 4 16:45:59 2008: 00000130: 1a
44 5e 1e e7 c1 c5 ae c2 6f e7 ca 63 31 5f 3a
.D^.....o..c1_: Tue Mar 4 16:45:59 2008: 00000140: cf
a9 da 83 0e c8 94 93 35 2e c8 f1 21 b0 78 1c
.....5...!.x. Tue Mar 4 16:45:59 2008: 00000150: a1
ca f7 e9 40 a7 d1 7a f1 85 d6 e9 36 46 51 a7
....@..z....6FQ. Tue Mar 4 16:45:59 2008: 00000160: a7
bf 70 db a7 47 da db 59 69 17 db 06 a3 7e b1
..p..G..Yi....~. Tue Mar 4 16:45:59 2008: 00000170: 3c
e5 ad 39 7f ee 61 cd ab 3e 0e 8a d5 c1 47 d4
<..9..a..>....G. Tue Mar 4 16:45:59 2008: 00000180: 65
62 09 22 f4 75 c5 5b b1 42 94 14 9f c7 02 03
eb."u.[.B..... Tue Mar 4 16:45:59 2008: 00000190: 01
00 01 a3 82 01 97 30 82 01 93 30 0e 06 03 55
.....0...0...U Tue Mar 4 16:45:59 2008: 000001a0: 1d
0f 01 01 ff 04 04 03 02 04 f0 30 44 06 09 2a
.....0D..* Tue Mar 4 16:45:59 2008: 000001b0: 86
48 86 f7 0d 01 09 0f 04 37 30 35 30 0e 06 08
.H.....7050... Tue Mar 4 16:45:59 2008: 000001c0: 2a
86 48 86 f7 0d 03 02 02 02 00 80 30 0e 06 08
*.H.....0... Tue Mar 4 16:45:59 2008: 000001d0: 2a
86 48 86 f7 0d 03 04 02 02 00 80 30 07 06 05
*.H.....0... Tue Mar 4 16:45:59 2008: 000001e0: 2b
0e 03 02 07 30 0a 06 08 2a 86 48 86 f7 0d 03
+....0...*.H.... Tue Mar 4 16:45:59 2008: 000001f0: 07
30 1d 06 03 55 1d 0e 04 16 04 14 b3 fe c9 de
.0...U..... Tue Mar 4 16:45:59 2008: 00000200: 52
60 44 c8 9a c2 4a c2 b4 fd 98 2c 8b 39 5a a6
R`D...J.....,9Z. Tue Mar 4 16:45:59 2008: 00000210: 30
13 4f ff 06 03 55 1d 25 04 0c 30 0a 06 08 2b
0.O...U.%.0...+ Tue Mar 4 16:45:59 2008: 00000220: 06
01 05 05 07 03 01 30 1f 06 03 55 1d 23 04 18
.....0...U.#.. Tue Mar 4 16:45:59 2008: 00000230: 30
16 80 14 f0 a4 3a c2 cd f5 d4 c8 b4 5e ee 03

0.....^.. Tue Mar 4 16:45:59 2008: 00000240: 4f
83 79 b1 f2 d4 e0 19 30 5f 06 03 55 1d 1f 04
O.y.....0...U... Tue Mar 4 16:45:59 2008: 00000250: 58
30 56 30 54 a0 52 a0 50 86 25 68 74 74 70 3a
XOV0T.R.P.%http: Tue Mar 4 16:45:59 2008: 00000260: 2f
2f 77 63 73 77 69 6e 2f 43 65 72 74 45 6e 72
//wswin/CertEnr Tue Mar 4 16:46:00 2008: 00000270: 6f
6c 6c 2f 41 41 52 4f 4e 4c 41 42 2e 63 72 6c
oll/AARONLAB.crl Tue Mar 4 16:46:00 2008: 00000280: 86
27 66 69 6c 65 3a 2f 2f 5c 5c 77 63 73 77 69
'file://\\wswi Tue Mar 4 16:46:00 2008: 00000290: 6e
5c 43 65 72 74 45 6e 72 6f 6c 6c 5c 41 41 52
n\CertEnroll\AAR Tue Mar 4 16:46:00 2008: 000002a0: 4f
4e 4c 41 42 2e 63 72 6c 30 81 84 06 08 2b 06
ONLAB.crl0....+. Tue Mar 4 16:46:00 2008: 000002b0: 01
05 05 07 01 01 04 78 30 76 30 38 06 08 2b 06
.....x0v08...+. Tue Mar 4 16:46:00 2008: 000002c0: 01
05 05 07 30 02 86 2c 68 74 74 70 3a 2f 2f 77
....0...,http://w Tue Mar 4 16:46:00 2008: 000002d0: 63
73 77 69 6e 2f 43 65 72 74 45 6e 72 6f 6c 6c
cswin/CertEnroll Tue Mar 4 16:46:00 2008: 000002e0: 2f
77 63 73 77 69 6e 5f 41 41 52 4f 4e 4c 41 42
/wswin_AARONLAB Tue Mar 4 16:46:00 2008: 000002f0: 2e
63 72 74 30 3a 06 08 2b 06 01 05 05 07 30 02
.crt0:...+.....0. Tue Mar 4 16:46:00 2008: 00000300: 86
2e 66 69 6c 65 3a 2f 2f 5c 5c 77 63 73 77 69
..file://\\wswi Tue Mar 4 16:46:00 2008: 00000310: 6e
4f ff 5c 43 65 72 74 45 6e 72 6f 6c 6c 5c 77
nO.\CertEnroll\w Tue Mar 4 16:46:00 2008: 00000320: 63
73 77 69 6e 5f 41 41 52 4f 4e 4c 41 42 2e 63
cswin_AARONLAB.c Tue Mar 4 16:46:00 2008: 00000330: 72
74 30 0d 06 09 2a 86 48 86 f7 0d 01 01 05 05
rt0...*.H..... Tue Mar 4 16:46:00 2008: 00000340: 00
03 82 01 01 00 67 35 f2 80 42 b5 a8 be f7 c4
.....g5..B..... Tue Mar 4 16:46:00 2008: 00000350: 9b
ea 19 10 67 39 78 cb 38 fb 36 15 69 2a f0 80
....g9x.8.6.i*.. Tue Mar 4 16:46:00 2008: 00000360: 1e
a1 7d 63 72 6a e0 7e d4 51 7a 1d 64 ec ee b5
..)crj.~.Qz.d... Tue Mar 4 16:46:00 2008: 00000370: 2a
73 dc b0 d1 eb 0f 28 1d 66 7a bc 12 ef d8 61
*s.....(fz....a Tue Mar 4 16:46:00 2008: 00000380: 5d
05 7b 81 0f 57 20 4d 49 37 4d ba 0b 5a 96 65
].{.W.MI7M..Z.e Tue Mar 4 16:46:00 2008: 00000390: d6
a8 e1 bb 1f c6 0e 27 4c 4b d6 3a 00 c7 8d 83
.....'LK:..... Tue Mar 4 16:46:00 2008: 000003a0: 22
a5 29 61 36 19 19 33 f2 41 18 f7 c6 42 23 36
".)a6..3.A...B#6 Tue Mar 4 16:46:00 2008: 000003b0: 92
66 4a d9 ef fa 32 d7 a5 0a df 47 50 3c 72 23
..fJ...2....GP<r# Tue Mar 4 16:46:00 2008: 000003c0: f0
0a d5 59 eb a8 79 f2 e0 56 a0 97 91 48 60 31
...Y..y..V...H`1 Tue Mar 4 16:46:00 2008: 000003d0: 56
8d 2f b2 69 45 e5 44 3a 59 13 dd 66 eb c7 58
V./.iE.D:Y..f..X Tue Mar 4 16:46:00 2008: 000003e0: 35
90 7c 79 69 ee dc 6e 19 68 b3 c3 4c ba 7d b3
5.|yi..n.h..L.}. Tue Mar 4 16:46:00 2008: 000003f0: 8f
a0 b9 e0 cf df 67 93 6f 01 d4 34 33 86 b6 95
.....g.o..43... Tue Mar 4 16:46:00 2008: 00000400: 77
1b 19 61 34 46 82 4c 8e 6b b4 6b e2 4a c1 20
w..a4F.L.k.k.J.. Tue Mar 4 16:46:00 2008: 00000410: 18
1d 45 41 50 3d 30 2e 32 30 32 2e 32 37 65 61
..EAP=0.202.27ea Tue Mar 4 16:46:00 2008: 00000420: 2e
32 3b 53 56 43 3d 30 2e 36 34 37 3b 50 12 3a
..2;SVC=0.647;P.: Tue Mar 4 16:46:00 2008: 00000430: f3
3b 7f 99 45 f4 e6 a6 29 c4 17 51 ce 97 df

```
.;.E...).Q... Tue Mar 4 16:46:00 2008: ****Enter
processIncomingMessages: response code=11 Tue Mar 4
16:46:00 2008: ****Enter processRadiusResponse: response
code=11 Tue Mar 4 16:46:00 2008: 00:19:56:b0:7e:b6
Access-Challenge received from RADIUS server 10.0.47.42
for mobile 00:19:56:b0: 7e:b6 receiveId = 7 Tue Mar 4
16:46:00 2008: 00:19:56:b0:7e:b6 Processing Access-
Challenge for mobile 00:19:56:b0:7e:b6 Tue Mar 4
16:46:00 2008: 00:19:56:b0:7e:b6 Entering Backend Auth
Req state (id=178) for mobile 00:19:56:b0:7e:b6 Tue Mar
4 16:46:00 2008: 00:19:56:b0:7e:b6 Sending EAP Request
from AAA to mobile 00:19:56:b0:7e:b6 (EAP Id 178) Tue
Mar 4 16:46:00 2008: 00:19:56:b0:7e:b6 Received EAPOL
EAPPKT from mobile 00:19:56:b0:7e:b6 Tue Mar 4 16:46:00
2008: 00:19:56:b0:7e:b6 Received EAP Response from
mobile 00:19:56:b0:7e:b6 (EAP Id 178, EAP Type 13) Tue
Mar 4 16:46:00 2008: 00:19:56:b0:7e:b6 Entering Backend
Auth Response state for mobile 00:19:56:b0:7e:b6 Tue Mar
4 16:46:00 2008: 00:19:56:b0:7e:b6 Successful
transmission of Authentication Packet (id 20) to
10.0.47.42:1812, proxy state 00:19:56:b0:7e:b6-00:00 Tue
Mar 4 16:46:00 2008: 00000000: 01 14 00 b7 e8 b0 94 59
96 a1 7f e5 af 22 0f 6c .....Y.....".l Tue Mar 4
16:46:00 2008: 00000010: 1e 33 6e ee 01 05 57 47 42 1f
13 30 30 2d 31 39 .3n...WGB..00-19 Tue Mar 4 16:46:00
2008: 00000020: 2d 35 36 2d 42 30 2d 37 45 2d 42 36 1e
1a 30 30 -56-B0-7E-B6..00 Tue Mar 4 16:46:00 2008:
00000030: 2d 31 39 2d 41 39 2d 34 32 2d 45 34 2d 31 30
3a -19-A9-42-E4-10: Tue Mar 4 16:46:00 2008: 00000040:
45 41 50 54 4c 53 05 06 00 00 00 04 04 06 0a 00
EAPTLS..... Tue Mar 4 16:46:00 2008: 00000050: 2f
06 20 10 74 75 63 73 6f 6e 2d 77 6c 63 32 30 /...tucson-
wlc20 Tue Mar 4 16:46:00 2008: 00000060: 30 36 1a 0c 00
00 37 63 01 06 00 00 00 06 06 06 06....7c..... Tue
Mar 4 16:46:00 2008: 00000070: 00 00 00 02 0c 06 00 00
05 14 3d 06 00 00 00 13 .....=..... Tue Mar 4
16:46:00 2008: 00000080: 4f 08 02 b2 00 06 0d 00 18 1d
45 41 50 3d 30 2e O.....EAP=0. Tue Mar 4 16:46:00
2008: 00000090: 32 30 32 2e 32 37 65 61 2e 32 3b 53 56
43 3d 30 202.27ea.2;SVC=0 Tue Mar 4 16:46:00 2008:
000000a0: 2e 36 34 37 3b 50 12 a2 aa c7 ed 12 84 25 db
4b .647;P.....%.K Tue Mar 4 16:46:00 2008: 000000b0:
4c dc 45 09 06 44 c6 L.E..D. Tue Mar 4 16:46:00 2008:
00000000: 0b 14 04 04 6b 98 3a 74 12 1f 77 54 77 d8 a8
77 ....k.:t..wTw..w Tue Mar 4 16:46:00 2008: 00000010:
4e a8 a7 6b 4f ff 01 b3 03 b9 0d 00 c6 87 1d b6
N..kO..... Tue Mar 4 16:46:00 2008: 00000020: 06
5b 24 67 26 09 ee 5f 9c 64 f3 a9 c1 99 49 3e
.[$g&..._d...I> Tue Mar 4 16:46:00 2008: 00000030: 2b
79 f1 57 17 65 6c 2f c4 09 4d 54 7d a4 67 91
+y.W.el/..MT}.g. Tue Mar 4 16:46:00 2008: 00000040: 48
59 ec aa 68 5b 0f 66 c5 e9 22 a6 09 8d 36 cf
HY..h[.f.."...6. Tue Mar 4 16:46:00 2008: 00000050: e3
d9 00 03 68 30 82 03 64 30 82 02 4c a0 03 02
....h0..d0..L... Tue Mar 4 16:46:00 2008: 00000060: 01
02 02 10 61 26 83 24 8d ba 53 9b 44 b0 39 bd
....a&$.S.D.9. Tue Mar 4 16:46:00 2008: 00000070: 51
cd 1d 48 30 0d 06 09 2a 86 48 86 f7 0d 01 01
Q..H0...*.H..... Tue Mar 4 16:46:00 2008: 00000080: 05
05 00 30 13 31 11 30 0f 06 03 55 04 03 13 08
...0.1.0...U... Tue Mar 4 16:46:00 2008: 00000090: 41
41 52 4f 4e 4c 41 42 30 1e 17 0d 30 38 30 32
AARONLAB0...0802 Tue Mar 4 16:46:00 2008: 000000a0: 32
38 32 33 33 34 34 38 5a 17 0d 31 38 30 32 32
```

28233448Z..18022 Tue Mar 4 16:46:00 2008: 000000b0: 38
32 33 34 31 32 35 5a 30 13 31 11 30 0f 06 03
8234125Z0.1.0... Tue Mar 4 16:46:00 2008: 000000c0: 55
04 03 13 08 41 41 52 4f 4e 4c 41 42 30 82 01
U....AARONLAB0.. Tue Mar 4 16:46:00 2008: 000000d0: 22
30 0d 06 09 2a 86 48 86 f7 0d 01 01 01 05 00
"0...*.H..... Tue Mar 4 16:46:00 2008: 000000e0: 03
82 01 0f 00 30 82 01 0a 02 82 01 01 00 c8 5a
.....0.....Z Tue Mar 4 16:46:00 2008: 000000f0: 57
75 45 19 4a 8b 99 da 35 6c cb e0 b6 a0 ff 66
WuE.J...5l.....f Tue Mar 4 16:46:00 2008: 00000100: e2
8f c1 44 89 09 32 13 c7 d8 70 6c 6d 74 2d e5
...D..2...plmt-. Tue Mar 4 16:46:00 2008: 00000110: 89
b8 23 4f ff ea 0a 0e 2d 57 1b 62 36 05 90 92 ..#0....-
W.b6... Tue Mar 4 16:46:00 2008: 00000120: e0 ea f9 a3
e2 fb 54 87 f4 cf 69 52 86 be 0b caT...iR.... Tue
Mar 4 16:46:00 2008: 00000130: 14 d1 88 9d 82 01 9a f7
08 da ba cc c9 29 37 94))7. Tue Mar 4
16:46:00 2008: 00000140: 27 75 d4 6e ae 9e 60 06 84 94
9b 42 f6 c7 5e e0 'u.n..'....B..^. Tue Mar 4 16:46:00
2008: 00000150: 29 34 b3 06 cb 24 b1 39 73 84 ba be ba
d8 6f bb)4...\$.9s.....o. Tue Mar 4 16:46:00 2008:
00000160: 94 f9 32 36 d6 68 68 f2 b2 43 e6 0e a9 b6 4b
62 ..26.hh..C....Kb Tue Mar 4 16:46:00 2008: 00000170:
b8 f9 6e 47 dc 0e c5 5b 16 a3 94 e9 96 08 e5 18
..nG...[..... Tue Mar 4 16:46:00 2008: 00000180: f0
38 ad a2 98 d3 7c 73 39 80 4a ae 14 e3 f8 f7
.8....|s9.J.... Tue Mar 4 16:46:00 2008: 00000190: 1e
14 27 bb 6a ce a1 2a dc 18 66 59 ea b4 d9 b1
..'j...*.fy.... Tue Mar 4 16:46:00 2008: 000001a0: a7
50 e9 ff 56 09 ea 93 df 31 08 09 17 ab e5 e9
.P..V....1..... Tue Mar 4 16:46:00 2008: 000001b0: 80
90 30 95 e4 54 90 75 bc f0 7f 13 b1 e7 cd 0b
..0..T.u..... Tue Mar 4 16:46:00 2008: 000001c0: 88
33 81 e7 74 d2 81 d9 97 ab b2 57 f4 5f f6 8b
.3..t.....W._.. Tue Mar 4 16:46:00 2008: 000001d0: 1e
c2 62 d4 de 94 74 7f 8a 28 3b 64 73 88 86 28
..b...t...(;ds..(Tue Mar 4 16:46:00 2008: 000001e0: 92
74 b0 92 94 7e ce e1 74 23 f2 64 da 9a 88 47
.t...~...t#.d...G Tue Mar 4 16:46:00 2008: 000001f0: 02
03 01 00 01 a3 81 b3 30 81 b0 30 0b 06 03 55
.....0..0...U Tue Mar 4 16:46:00 2008: 00000200: 1d
0f 04 04 03 02 01 86 30 0f 06 03 55 1d 13 01
.....0...U... Tue Mar 4 16:46:00 2008: 00000210: 01
ff 4f ff 04 05 30 03 01 01 ff 30 1d 06 03 55
..O...0....0...U Tue Mar 4 16:46:00 2008: 00000220: 1d
0e 04 16 04 14 f0 a4 3a c2 cd f5 d4 c8 b4 5e
.....:.....^ Tue Mar 4 16:46:00 2008: 00000230: ee
03 4f 83 79 b1 f2 d4 e0 19 30 5f 06 03 55 1d
..O.y.....0_..U. Tue Mar 4 16:46:00 2008: 00000240: 1f
04 58 30 56 30 54 a0 52 a0 50 86 25 68 74 74
..X0V0T.R.P.%htt Tue Mar 4 16:46:00 2008: 00000250: 70
3a 2f 2f 77 63 73 77 69 6e 2f 43 65 72 74 45
p://wswin/CertE Tue Mar 4 16:46:00 2008: 00000260: 6e
72 6f 6c 6c 2f 41 41 52 4f 4e 4c 41 42 2e 63
nroll/AARONLAB.c Tue Mar 4 16:46:00 2008: 00000270: 72
6c 86 27 66 69 6c 65 3a 2f 2f 5c 5c 77 63 73
rl.'file://\\wcs Tue Mar 4 16:46:00 2008: 00000280: 77
69 6e 5c 43 65 72 74 45 6e 72 6f 6c 6c 5c 41
win\CertEnroll\A Tue Mar 4 16:46:00 2008: 00000290: 41
52 4f 4e 4c 41 42 2e 63 72 6c 30 10 06 09 2b
ARONLAB.crl0...+ Tue Mar 4 16:46:00 2008: 000002a0: 06
01 04 01 82 37 15 01 04 03 02 01 00 30 0d 06
.....7.....0.. Tue Mar 4 16:46:00 2008: 000002b0: 09


```
2a 86 48 86 f7 0d 01 01 05 05 00 03 82 01 01
.*.H..... Tue Mar 4 16:46:00 2008: 000002c0: 00
17 eb b2 43 da 02 66 05 cd 76 c0 7b 2a 16 83
....C..f..v.{*.. Tue Mar 4 16:46:00 2008: 000002d0: 95
bb 5e bf d3 db fc 23 7e 14 6e 52 f8 37 01 7c
..^.....#~.nR.7.| Tue Mar 4 16:46:00 2008: 000002e0: dd
e9 bf 34 60 49 f1 68 7e da 53 07 f6 b2 66 6d
...4`I.h~.S...fm Tue Mar 4 16:46:00 2008: 000002f0: 8c
bd ca 26 f4 fa 3d 03 4f db be 92 33 7e 50 06
...&..=.O...3~P. Tue Mar 4 16:46:00 2008: 00000300: 5e
b3 b9 35 c6 83 3c 90 1e 42 54 3e 63 17 9a 8a
^..5...<..BT>c... Tue Mar 4 16:46:00 2008: 00000310: d0
4f c4 68 24 97 90 a1 77 c9 c8 93 1f 58 ab ca
.O.h$....w....X.. Tue Mar 4 16:46:00 2008: 00000320: f7
18 e6 8c 36 12 44 9d a6 ca 43 5f 03 07 16 99
....6.D...C_.... Tue Mar 4 16:46:00 2008: 00000330: 1d
a4 48 7d a4 e5 12 7c d0 81 e7 35 9e ad 69 5e
..H)...|...5...i^ Tue Mar 4 16:46:00 2008: 00000340: 15
d7 2a 7f 51 4e 8c 59 69 9f d1 41 9b 2e e1 05
..*.QN.Yi..A.... Tue Mar 4 16:46:00 2008: 00000350: 95
15 bd b1 1a 97 a6 69 d3 9c 0b 93 00 16 e1 49
.....i.....I Tue Mar 4 16:46:00 2008: 00000360: 66
e3 98 29 79 ba 14 69 cf 76 27 69 7d 43 d0 f4
f..)y...i.v'i)C.. Tue Mar 4 16:46:00 2008: 00000370: 86
3c 6b 58 55 d4 85 be c5 da 71 e4 43 76 3d 0a
.<kXU.....q.Cv=. Tue Mar 4 16:46:00 2008: 00000380: d3
4f 49 97 12 75 e3 7d 88 92 99 5d fc 7a 69 28
.OI..u.}...].zi( Tue Mar 4 16:46:00 2008: 00000390: f6
f0 20 70 33 b7 22 5a bf c5 e5 28 43 35 00 2f
...p3."Z...(C5./ Tue Mar 4 16:46:00 2008: 000003a0: 47
46 9a 5a 45 5c 56 d5 24 3d 44 bf e9 63 f2 05
GF.ZE\V.$=D..c.. Tue Mar 4 16:46:01 2008: 000003b0: 84
da 94 17 b7 ef c3 31 7d 04 30 87 e1 c3 31 8a
.....1}.0...1. Tue Mar 4 16:46:01 2008: 000003c0: 2a
e1 52 16 03 01 00 0d 0d 00 00 05 02 01 02 00
*.R..... Tue Mar 4 16:46:01 2008: 000003d0: 00
0e 00 00 00 18 1d 45 41 50 3d 30 2e 32 30 32
.....EAP=0.202 Tue Mar 4 16:46:01 2008: 000003e0: 2e
32 37 65 61 2e 33 3b 53 56 43 3d 30 2e 36 34
.27ea.3;SVC=0.64 Tue Mar 4 16:46:01 2008: 000003f0: 37
3b 50 12 05 0e 3c e0 e4 5f 38 21 96 26 8e 39
7;P...<..._8!.&.9 Tue Mar 4 16:46:01 2008: 00000400: 96
a9 09 5d...] Tue Mar 4 16:46:01 2008: ****Enter
processIncomingMessages: response code=11 Tue Mar 4
16:46:01 2008: ****Enter processRadiusResponse: response
code=11 Tue Mar 4 16:46:01 2008: 00:19:56:b0:7e:b6
Access-Challenge received from RADIUS server 10.0.47.42
for mobile 00:19:56:b0: 7e:b6 receiveId = 7 Tue Mar 4
16:46:01 2008: 00:19:56:b0:7e:b6 Processing Access-
Challenge for mobile 00:19:56:b0:7e:b6 Tue Mar 4
16:46:01 2008: 00:19:56:b0:7e:b6 Entering Backend Auth
Req state (id=179) for mobile 00:19:56:b0:7e:b6 Tue Mar
4 16:46:01 2008: 00:19:56:b0:7e:b6 Sending EAP Request
from AAA to mobile 00:19:56:b0:7e:b6 (EAP Id 179) Tue
Mar 4 16:46:01 2008: 00:19:56:b0:7e:b6 Received EAPOL
EAPPKT from mobile 00:19:56:b0:7e:b6 Tue Mar 4 16:46:01
2008: 00:19:56:b0:7e:b6 Received EAP Response from
mobile 00:19:56:b0:7e:b6 (EAP Id 179, EAP Type 13) Tue
Mar 4 16:46:01 2008: 00:19:56:b0:7e:b6 Entering Backend
Auth Response state for mobile 00:19:56:b0:7e:b6 Tue Mar
4 16:46:01 2008: 00:19:56:b0:7e:b6 Successful
transmission of Authentication Packet (id 21) to
10.0.47.42:1812, proxy state 00:19:56:b0:7e:b6-00:00 Tue
Mar 4 16:46:01 2008: 00000000: 01 15 05 76 81 b7 fa 95
```

63 1f 50 6f 98 4d a3 6b ...v....c.Po.M.k Tue Mar 4
16:46:01 2008: 00000010: db 3c bc 1d 01 05 57 47 42 1f
13 30 30 2d 31 39 .<...WGB..00-19 Tue Mar 4 16:46:01
2008: 00000020: 2d 35 36 2d 42 30 2d 37 45 2d 42 36 1e
1a 30 30 -56-B0-7E-B6..00 Tue Mar 4 16:46:01 2008:
00000030: 2d 31 39 2d 41 39 2d 34 32 2d 45 34 2d 31 30
3a -19-A9-42-E4-10: Tue Mar 4 16:46:01 2008: 00000040:
45 41 50 54 4c 53 05 06 00 00 00 04 04 06 0a 00
EAPTLS..... Tue Mar 4 16:46:01 2008: 00000050: 2f
06 20 10 74 75 63 73 6f 6e 2d 77 6c 63 32 30 /...tucson-
wlc20 Tue Mar 4 16:46:01 2008: 00000060: 30 36 1a 0c 00
00 37 63 01 06 00 00 00 06 06 06 06....7c..... Tue
Mar 4 16:46:01 2008: 00000070: 00 00 00 02 0c 06 00 00
05 14 3d 06 00 00 00 13=..... Tue Mar 4
16:46:01 2008: 00000080: 4f ff 02 b3 04 bd 0d 80 00 00
04 b3 16 03 01 03 O..... Tue Mar 4 16:46:01
2008: 00000090: 6d 0b 00 03 69 00 03 66 00 03 63 30 82
03 5f 30 m...i..f..c0.._0 Tue Mar 4 16:46:01 2008:
000000a0: 82 02 47 a0 03 02 01 02 02 0a 13 79 b0 72 00
00 ..G.....y.r.. Tue Mar 4 16:46:01 2008: 000000b0:
00 00 00 0c 30 0d 06 09 2a 86 48 86 f7 0d 01 01
....0...*.H.... Tue Mar 4 16:46:01 2008: 000000c0: 05
05 00 30 13 31 11 30 0f 06 03 55 04 03 13 08
...0.1.0...U.... Tue Mar 4 16:46:01 2008: 000000d0: 41
41 52 4f 4e 4c 41 42 30 1e 17 0d 30 38 30 33
AARONLAB0...0803 Tue Mar 4 16:46:01 2008: 000000e0: 30
33 31 38 33 33 30 39 5a 17 0d 30 39 30 33 30
03183309Z..09030 Tue Mar 4 16:46:01 2008: 000000f0: 33
31 38 34 33 30 39 5a 30 0e 31 0c 30 0a 06 03
3184309Z0.1.0... Tue Mar 4 16:46:01 2008: 00000100: 55
04 03 13 03 57 47 42 30 81 9f 30 0d 06 09 2a
U...WGB0..0...* Tue Mar 4 16:46:01 2008: 00000110: 86
48 86 f7 0d 01 01 01 05 00 03 81 8d 00 30 81
.H.....0. Tue Mar 4 16:46:01 2008: 00000120: 89
02 81 81 00 a6 34 91 20 dd 58 df b2 60 c0 6c
.....4...X..`l Tue Mar 4 16:46:01 2008: 00000130: d0
9d 10 86 01 a9 61 9f cb 2b 01 22 49 d7 38 ee
.....a..+."I.8. Tue Mar 4 16:46:01 2008: 00000140: 00
fe be c9 cd 48 4b 73 a0 75 6d bb d0 c9 20 24
.....HKs.um....\$ Tue Mar 4 16:46:01 2008: 00000150: 0f
cc f0 76 2f ad ef 43 53 8f b7 ec c7 50 04 02
...v/..CS...P.. Tue Mar 4 16:46:01 2008: 00000160: d8
03 4a 7d 08 9e b4 f2 78 ab 36 06 ba f7 02 ab
..J}....x.6..... Tue Mar 4 16:46:01 2008: 00000170: a1
6e 26 6c 2d d4 10 08 0d 25 82 1a d2 fc 14 4f .n&l-
....%.O Tue Mar 4 16:46:01 2008: 00000180: ff 86 fa
fd 84 ec de be 3c 3e f8 be d6 b6 7b 81<>....{.
Tue Mar 4 16:46:01 2008: 00000190: 89 9a da a6 96 fd 7f
e7 dd bf 7f 26 6e 20 03 63&n..c Tue Mar 4
16:46:01 2008: 000001a0: c4 a2 56 4c 8e 75 99 02 03 01
00 01 a3 82 01 3c ..VL.u.....< Tue Mar 4 16:46:01
2008: 000001b0: 30 82 01 38 30 0e 06 03 55 1d 0f 01 01
ff 04 04 0..80...U..... Tue Mar 4 16:46:01 2008:
000001c0: 03 02 05 a0 30 1d 06 03 55 1d 0e 04 16 04 14
410...U.....A Tue Mar 4 16:46:01 2008: 000001d0:
97 b6 32 83 7f c0 88 11 4d 59 d5 44 70 e9 0f c6
..2.....MY.Dp... Tue Mar 4 16:46:01 2008: 000001e0: 3b
a2 85 30 1f 06 03 55 1d 23 04 18 30 16 80 14
;..0...U.#..0... Tue Mar 4 16:46:01 2008: 000001f0: f0
a4 3a c2 cd f5 d4 c8 b4 5e ee 03 4f 83 79 b1
...:.....^..O.y. Tue Mar 4 16:46:01 2008: 00000200: f2
d4 e0 19 30 5f 06 03 55 1d 1f 04 58 30 56 30
....0...U...X0V0 Tue Mar 4 16:46:01 2008: 00000210: 54
a0 52 a0 50 86 25 68 74 74 70 3a 2f 2f 77 63

```

T.R.P.%http://wc Tue Mar 4 16:46:01 2008: 00000220: 73
77 69 6e 2f 43 65 72 74 45 6e 72 6f 6c 6c 2f
swin/CertEnroll/ Tue Mar 4 16:46:01 2008: 00000230: 41
41 52 4f 4e 4c 41 42 2e 63 72 6c 86 27 66 69
AARONLAB.crl.'fi Tue Mar 4 16:46:01 2008: 00000240: 6c
65 3a 2f 2f 5c 5c 77 63 73 77 69 6e 5c 43 65
le://\\wswin\Ce Tue Mar 4 16:46:01 2008: 00000250: 72
74 45 6e 72 6f 6c 6c 5c 41 41 52 4f 4e 4c 41
rtEnroll\AARONLA Tue Mar 4 16:46:01 2008: 00000260: 42
2e 63 72 6c 30 81 84 06 08 2b 06 01 05 05 07
B.crl0....+..... Tue Mar 4 16:46:01 2008: 00000270: 01
01 04 78 30 76 30 38 06 08 2b 06 01 05 4f ff
...x0v08...+...0. Tue Mar 4 16:46:01 2008: 00000280: 05
07 30 02 86 2c 68 74 74 70 3a 2f 2f 77 63 73
..0.,http://wcs Tue Mar 4 16:46:01 2008: 00000290: 77
69 6e 2f 43 65 72 74 45 6e 72 6f 6c 6c 2f 77
win/CertEnroll/w Tue Mar 4 16:46:01 2008: 000002a0: 63
73 77 69 6e 5f 41 41 52 4f 4e 4c 41 42 2e 63
cswin_AARONLAB.c Tue Mar 4 16:46:01 2008: 000002b0: 72
74 30 3a 06 08 2b 06 01 05 05 07 30 02 86 2e
rt0:...+.....0... Tue Mar 4 16:46:01 2008: 000002c0: 66
69 6c 65 3a 2f 2f 5c 5c 77 63 73 77 69 6e 5c
file://\\wswin\ Tue Mar 4 16:46:01 2008: 000002d0: 43
65 72 74 45 6e 72 6f 6c 6c 5c 77 63 73 77 69
CertEnroll\wswi Tue Mar 4 16:46:01 2008: 000002e0: 6e
5f 41 41 52 4f 4e 4c 41 42 2e 63 72 74 30 0d
n_AARONLAB.crt0. Tue Mar 4 16:46:01 2008: 000002f0: 06
09 2a 86 48 86 f7 0d 01 01 05 05 00 03 82 01
..*.H..... Tue Mar 4 16:46:01 2008: 00000300: 01
00 2e a1 3f f3 52 52 97 b5 83 43 0f 61 20 64
....?.RR...C.a.d Tue Mar 4 16:46:01 2008: 00000310: 40
fd d3 16 38 4f d9 5f 64 94 a7 c2 59 53 53 52
@...80._d...YSSR Tue Mar 4 16:46:01 2008: 00000320: 90
5d ee 1c e0 2a 90 af f4 e8 51 3e 87 38 9a ce
.]...*....Q>.8.. Tue Mar 4 16:46:01 2008: 00000330: 88
0c 4f 1f ad f1 ef dd 96 44 6b 51 4e 9f 2c a1
..O.....DkQN.,. Tue Mar 4 16:46:01 2008: 00000340: 8a
c5 0e bd d0 f9 7e 34 fa 22 67 26 e1 26 e6 3e
.....~4."g&.&.> Tue Mar 4 16:46:01 2008: 00000350: bd
b8 9f 64 f0 65 6f 23 f0 67 40 60 0f 4b f1 ff
...d.eo#.g@`.K.. Tue Mar 4 16:46:01 2008: 00000360: c1
9c 3c 11 81 be b2 7a 45 b6 bd f2 26 76 2a 3a
..<....zE...&v*: Tue Mar 4 16:46:01 2008: 00000370: 52
32 65 cf 62 0b 47 65 b4 b5 fa db b4 4f ff 07
R2e.b.Ge.....O.. Tue Mar 4 16:46:01 2008: 00000380: ae
54 58 11 d8 52 8f f8 e3 e5 00 f1 c4 1d 2a a4
.TX..R.....*.

```

[Related Information](#)

- [Workgroup Bridges in a Cisco Unified Wireless Network Configuration Example](#)
- [Wireless LAN Controller \(WLC\) Configuration Best Practices](#)
- [Technical Support & Documentation - Cisco Systems](#)